

10A - 10B COIL DATA

The lengths listed below do not include connecting wires from the coil to the coil form terminals. All coils are 1" diameter B & W Miniductor stock.

	<u>Mixer</u>	<u>Amplifier</u>
160M	37-3/4 #3016	38-3/4 #3016 Tap at 7-3/8 turns
80M	23-3/4 #3015	25-3/4 #3015 Tap at 3 1/2 turns
40M	13-3/4 #3015	13-3/4 #3015 Tap at 1-7/8 turns
20M	9-3/8 #3014	10-3/4 #3014 Tap at 1-3/8 turns
15M	5-3/4 #3014	5-3/4 #3014 Tap at 1 turn
10M	4-3/8 #3013	4-3/4 #3013 Tap at 5/8 turn

ZENITH SALES CORPORATION
5801 W. DICKENS AVE.
CHICAGO 39, ILL.

Printed in U.S.A.

5/13/65